

LED 2FT & 4FT Universal A + B

Direct Replacement For T12 & T8 Lamps



- Retrofit for T8 & T12 Fluorescent Tube
- 50,000 Hours Rated Average Life
- 5 Year Warranty
- Uniformed and Consistent Color
- Highly Uniform Light Beams
- Wide Beam Design 320 Degree
- Saving Energy Up to 60%
- Environmentally Friendly (No Mercury/ No Lead/No UV)
- CUL & Listed - Compliance to North American

CRI 85+
TRUE COLORS

DAMP LOCATION

320°

UL US LISTED
E366244

CLASSIFIED
UL US
E366680

FCC

DLC PREMIUM

Lifetime:
50 000 hours

Warranty:
5 years

| | ITEM | DESCRIPTION | COLOR TEMP | OUTPUT LUMEN | BEAM ANGLE | WATTAGE | EQUIV. WATTAGE | CRI | DIMMABLE | PACK | |
|------------------------------|--|-----------------|------------|--------------|------------|---------|----------------|-----|----------|------|--|
| Replaces: T12 & T8 | Frosted 2 feet Crack & shatter-proof | | | | | | | | | | |
| | G-83406 | F9T8/830/F/LED | 3000K | 1000 | 320 | 9 | 20W | >85 | No | 30 | |
| | G-19803 | F9T8/835/F/LED | 3500K | 1000 | 320 | 9 | 20W | >85 | No | 30 | |
| | G-83407 | F9T8/841/F/LED | 4100K | 1000 | 320 | 9 | 20W | >85 | No | 30 | |
| | G-83408 | F9T8/850/F/LED | 5000K | 1000 | 320 | 9 | 20W | >85 | No | 30 | |
| | G-83409 | F9T8/865/F/LED | 6500K | 1000 | 320 | 9 | 20W | >85 | No | 30 | |
| | Frosted 4 feet Crack & shatter-proof | | | | | | | | | | |
| | G-83402 | F18T8/830/F/LED | 3000K | 2300 | 320 | 18 | 40W | >85 | No | 30 | |
| | G-83401 | F18T8/835/F/LED | 3500K | 2400 | 320 | 18 | 40W | >85 | No | 30 | |
| | G-83403 | F18T8/841/F/LED | 4100K | 2400 | 320 | 18 | 40W | >85 | No | 30 | |
| G-83404 | F18T8/850/F/LED | 5000K | 2400 | 320 | 18 | 40W | >85 | No | 30 | | |
| G-83405 | F18T8/865/F/LED | 6500K | 2500 | 320 | 18 | 40W | >85 | No | 30 | | |
| Clear 2 feet Glass | | | | | | | | | | | |
| G-83457 | F9T8/841/C/LED | 4100K | 1000 | 320 | 9 | 20W | >85 | No | 30 | | |
| G-83458 | F9T8/850/C/LED | 5000K | 1000 | 320 | 9 | 20W | >85 | No | 30 | | |
| G-83459 | F9T8/865/C/LED | 6500K | 1000 | 320 | 9 | 20W | >85 | No | 30 | | |
| Clear 4 feet Glass | | | | | | | | | | | |
| G-83460 | F18T8/830/C/LED | 3000K | 2300 | 320 | 18 | 40W | >85 | No | 30 | | |
| G-83462 | F18T8/841/C/LED | 4100K | 2400 | 320 | 18 | 40W | >85 | No | 30 | | |
| G-83463 | F18T8/850/C/LED | 5000K | 2400 | 320 | 18 | 40W | >85 | No | 30 | | |
| G-83464 | F18T8/865/C/LED | 6500K | 2400 | 320 | 18 | 40W | >85 | No | 30 | | |

The diagram shows three wiring configurations for the LED tube lamp:

- Direct Replacement:** Shows the lamp connected to a standard AC line (L and N) with an Electronic Ballast in parallel.
- Bypass Ballast:** Shows the lamp connected to AC INPUT (L and N) with a Bypass Ballast in parallel.
- Bypass Ballast:** Shows the lamp connected to AC INPUT (L and N) with a Bypass Ballast in parallel.

Available Accessories

Emergency LED Driver

ITEM G-20230

26